MAINS FAIL TIMER

Versatile timer PCB

Link settings	L1 and L2 off	= 5 minute delay
	L2 on	= 10 minute delay
	L1 on	= 15 minute delay
	L1 and L2 on	= 20 minute delay

Connect 12v DC to neg and pos terminals, LED flashes quickly to indicate power is present

Connect any leg of 16v AC to TRIG terminal

No trigger link is required
The preset POT will not adjust the time settings

When AC power fails the unit begins timing and indicates this by turning the on board LED on,
Once timing has expired the relay will trigger for 10 seconds, the led will flash indicating the end of the timing cycle,
The LED continues to flash until AC is restored

N.C.
N.O.
COM
TRIG
NEG
POS



LINK1
LINK2